Passap Padded Seat Cushion – DM-80 & E6000

http://www.smokingneedles.net

Copyright © Smoking Needles Knitting 2001

This cushion takes less than an hour to knit and measures approx. 17" x 17". It uses small amounts of double stranded 2/24, Tamm 3- ply or any other comparable yarn. The one pictured was made with Tamm Star. You will also need a small bag of polyester fiberfill. The Passap combs and weights are optional.

Put 102 ndls in WP on each bed. L51-R51.
Handle down. Locks N/N. SS 3/3.
Knit 1 row. Hang combs and weights.
Locks CX/CX. SS 4/4. Knit 2 rows.
Locks N/N. SS 6/6. Knit 1 row.

RC 000
Set up pushers L50-R50 in 10 up, 10 down position across bed.

Duo80: Set back bed up exactly opposite. Pusher L51 and R51 should be opposite of adjacent needle. See diagram below.

Black strippers.
* Handle up. Locks BX <--/BX<--
Changing colors every 2 rows, knit 39 rows.
End with COL.

Drop bed and fill the 10 pockets with fiberfill across the bed.

Close beds. Handle down. Locks N/N. Knit 1 r.
DO NOT CHANGE COLORS ON THIS ROW!! *

Starting with the same color you just ended with repeat * to * to RC 400.
End with N/N row.
Transfer all sts to back bed. Bind off loosely.

E6000 Directions by Teryl Hollins

Pattern: 1000, KT 170, Enlarge sts x 10
Set up BB pushers the same as the FB pushers.

Tips:

Use comb & wts. Keep Handle DOWN for all rows. Orange strippers. Knit 29 rows, then stuff pockets, then knit 1 row N/N. Zero RC after each 30 rows.

Variations

One Color
Only use one color yarn. Stop every 29 rows to stuff the pockets, then do the N/N closing row. Repeat.

2 Color Vertical Tubes
Change colors every 2 rows, then stop every 29 rows to stuff the tubes. Do not do any N/N rows . Repeat.

Paillette Stuffed pockets
Use one normal yarn and one thin yarn.
Knit 29 rows, changing yarns every 2 rows.
Put a ¾" paillette into the thin yarn pockets, then do the N/N closing row. Repeat.

DIAG. E6000 pushers setup

```
      1          1111111111          1
       1111111111          1111111111

BX ← 11111111111111111111111111111111
LX   11111111111111111111111111111111

       1111111111          1111111111
      1          1111111111          1
```

DIAG. DUO-80 pushers setup

```
       1          1111111111          1
        1111111111          1111111111

 BX ← 11111111111111111111111111111111
 BX ← 11111111111111111111111111111111

        1          1111111111          1
       1111111111          1111111111
```